

# Recommended Pad Dimension

Hokuriku Electric Industry Co.,Ltd



## 【Recommended footprint】

Size (mm)	Model No.	A Dimension	B Dimension	W Dimension
0402	CR04, CRES04	0.20	0.50	0.20
0603	CR06, CRES06, CR06H	0.36	1.00	0.40
1005	CR10, FCL10, CRES10, CRS10, LCR10	0.60	2.00	0.70
1608	CR16, PCR16, CRES16, SCR16, ECR16, FCR16, UCR16, CRS16, LCR16	1.00	3.00	1.20
2012	CR20, CRES20, HCR20, SCR20, ECR20, FCR20, UCR20, CRS20, LCR20	1.20	4.00	1.65
3216	CR32, CRES32, HCR32, SCR32, ECR32, FCR32, CRS32, LCR32	2.20	5.00	2.00
3225	CR35, CRES35, SCR35, FCR35, CRS35, LCR35	2.20	4.70	2.90
5025	CR50, CRES50, HCR50, SCR50, FCR50, CRS50, LCR50	3.20	6.60	3.00
6432	CR64, CRES64, SCR64, LCR64	4.20	8.20	3.70
1632	WCRES32, WECR32, WLGR32, WCR32	0.65	2.65	3.2
2550	WCRES50, WECR50, WLGR50, WCR50	1.3	4	5
3264	WCRES64, WECR64, WLGR64, WCR64	1.45	4.85	6.4

\* Design\*specification are subject to change without prior notice. Please check before purchase and use.

HOKURIKU